

Serial Settings are as Follows:


Baud Rate:	115200
Data Bits:	8
Parity:	None
Stop Bits:	1

Straight cable to be used.

Key Commands

Command Suffix - Line Feed (0x0A), Carriage Return (0x0D)

Command	Description	Parameters	Example	Return
TON	Turn on the display	Integer (volume level)	"TON 10",0x0A,0x0D	#TV will be turned on
TOF	Turn off the display	None	"TOF",0x0A,0x0D	#TV will be sent to Active Standby state
GETQUICKSTANDBY	Returns quickstandby state (on/off)	None	"GETQUICKSTANDBY",0x0A,0x0D	#*Quick Standby is ...
VOLUMEUP	Increases volume level by 1 step	None	"VOLUMEUP",0x0A,0x0D	#*volume LEVEL is increased to ...
VOLUMEDOWN	Decrease volume level by 1 step	None	"VOLUMEDOWN",0x0A,0x0D	#*volume LEVEL is decreased to ...
VOLUME	Sets the volume to a specified level	Integer (volume level)	"VOLUME 50",0x0A,0x0D	#*set volume to (volume level)
SETMUTE	Sets mute value on/off	None	"SETMUTE",0x0A,0x0D	#*MUTE OFF OR #*MUTE ON
GETVOLUME	Returns volume	None	"GETVOLUME",0x0A,0x0D	#*volume is ...
GETMUTE	Returns mute (on/off)	None	"GETMUTE",0x0A,0x0D	#*MUTE OFF OR #*MUTE ON
SELECTSOURCE	Selects input source according to list below	Integer (input value)	"SELECTSOURCE 7",0x0A,0x0D	#*select TV source ...
	HDMI1: 7			
	HDMI2: 8			
	HDMI3: 9			
	HDMI4: 10			
	VGA: 12			
	Android: 18			
	Display Port: 19			
	OPS: 20			
GETSOURCE	Returns source	None	"GETSOURCE",0x0A,0x0D	#*source is ...

 See manual for full list of commands